


4-CHANNEL POWER AMPLIFIER

# KAC-742


## SERVICE MANUAL

# KENWOOD

©1991-2 PRINTED IN JAPAN  
B51-6281-00(T) 3326



CONNECTIONS







ADJUSTMENT

No.	ITEM	INPUT SETTINGS	OUTPUT SETTINGS	AMPLIFIER SETTINGS	ALIGNMENT POINTS	ALIGN FOR	FIG.
Connect a cassette deck.							
1	IDLE CURRENT	—	Connect a DC voltmeter between R131•R132 , R231•R232 R331•R332 , R431•R432	VOLUME: 0	VR102(L) VR202(R) VR302(L) VR402(R)	16mV	







# PC BOARD (Foil side view)





Refer to the schematic diagram for the values of resistors and capacitors.





KAC-742(K)



**CAUTION:** For continued safety, replace safety critical components only with manufacturer's recommended parts (refer to parts list). Indicates safety critical components. To reduce the risk of electric shock, leakage-current or resistance measurements shall be carried out (exposed parts are acceptably insulated from the supply circuit) before the appliance is returned to the customer.

DC voltages are as measured with a high impedance voltmeter. Values may vary slightly due to variations between individual instruments or/and units.

Les tensions c.c. doivent être mesurées avec un voltmètre à haute impédance. Les valeurs peuvent différer légèrement du fait des variations inhérentes aux appareils et aux instruments de mesure individuels.


Die angegebenen Gleichspannungswerte wurden mit einem hochohmigen Spannungsmesser gemessen. Dabei schwanken die Meßwerte aufgrund von Unterschieden zwischen einzelnen Instrumenten oder Geräten u.U. geringfügig.

Y08-4380-10

**KAC-742**  
**KENWOOD**



## EXPLODED VIEW



Parts with the exploded numbers larger than 700 are not supplied.

## PARTS LIST

### ✕ New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le **Parti No.** ne sont pas fournis.

**Teile ohne Parts No. werden nicht geliefert.**

Ref. No.	Address	New Parts	Parts No.	Description	Destination	Remarks		
参照番号	位置	新	部品番号	部品名 / 規格	仕向	備考		
KAC-742								
2	2A	*	A20-7674-08	PANEL ASSY	K ET			
3	2B	*	A23-5038-08	REAR PANEL				
3	2B	*	A23-5039-08	REAR PANEL				
5	1A	*	A40-1231-08	BOTTOM PLATE				
6	2A	*	B19-0874-08	LIGHTING BOARD	K ET			
-			B44-6006-04	BADGE				
-			B44-6007-04	BADGE				
-			B46-0100-20	WARRANTY CARD				
-		*	B64-0083-00	INSTRUCTION MANUAL				
-		*	B64-0084-00	INSTRUCTION MANUAL				
14	1A	*	E30-3676-08	RCA CORD			ET	
15	1A	*	E30-3677-08	DC CORD			ET	
16	3A	*	F01-1372-08	HEAT SINK				
F1	1B		F05-2531-05	FUSE (25A)				
-		*	H01-9265-08	ITEM CARTON BOX				
-		*	H03-3306-08	OUTER PACKING CASE				
-		*	H10-4375-08	POLYSTYRENE FOAMED FIXTURE (L)				
-		*	H10-4376-08	POLYSTYRENE FOAMED FIXTURE (R)				
-			H25-0336-04	PROTECT. BAG (inst. & warrant.				
-		*	H25-0341-04	PROTECTION BAG (for unit)				
35	1A	*	N99-1564-08	SCREW SET				
A	2A	*	N09-1945-05	SCREW (M3X8)				
B	2B		N09-4026-05	SCREW (4X8)				
C	2B		N15-1040-46	FLAT WASHER				
D	2A, 3B		N29-0053-05	LYLON RIVET				
E	1A, 1B		N35-3004-46	BINDING HEAD SCREW (M3X4)				
F	1B		N83-2608-45	BINDING HEAD SCREW (2.6X8)				
G	3A, 3B		N83-3005-45	BINDING HEAD SCREW (3X5)				
H	2A		N89-3006-45	BINDING HEAD TAPTITE (3X6)				
J	1A, 1B		N89-3008-45	BINDING HEAD TAPTITE (3X8)				
K	2A, 2B		N09-1467-05	SCREW (3X10)	ET			
36	1A		W01-0701-05	TARMINAL SET				
ELECTRIC CIRCUIT UNIT								
LED1			B30-1342-05	LED				
C1			CE04KW1E470M	ELECTRØ	47UF	25WV		
C2			C90-1634-05	ELECTRØ	3900UF	16WV		
C3 , 4			CF92FV1H104J	MF	0.10UF	J		
C5			CK45FB1H102K	CERAMIC	1000PF	K		
C6 , 7			CE04KW1E472M	ELECTRØ	4700UF	25WV		
C8			C90-2527-05	NP-ELECT	33UF	10WV		
C10			CF92FV1H102J	MF	1000PF	J		
C11			CE04KW1C100M	ELECTRØ	10UF	16WV		
C12			CE04KW1E470M	ELECTRØ	47UF	25WV		
C13			CE04KW1E101M	ELECTRØ	100UF	25WV		
C14			CK45FB1H472K	CERAMIC	4700PF	K		
C15			CE04KW1C330M	ELECTRØ	33UF	16WV		
C16 , 17			CE04KW1E470M	ELECTRØ	47UF	25WV		
C18			C90-2510-05	NP-ELECT	470UF	16WV		
C19			CE04KW1E471M	ELECTRØ	470UF	25WV		

**E:** Scandinavia & Europe    **K:** USA    **P:** Canada    **W:** Europe

**Y:** PX(Far East, Hawaii)    **T:** England    **M:** Other Areas

**Y: AAFES(Europe)      X: Australia**

 indicates safety critical components.

## PARTS LIST

\* New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

Ref. No.	Address	New Parts	Parts No.	Description	Destination	Remarks
参照番号	位置	新	部品番号	部品名 / 規格	仕向	備考
KAC-742						
2	2A	*	A20-7674-08	PANEL ASSY	K ET	
3	2B	*	A23-5038-08	REAR PANEL		
3	2B	*	A23-5039-08	REAR PANEL		
5	1A	*	A40-1231-08	BOTTOM PLATE		
6	2A	*	B19-0874-08	LIGHTING BOARD	K  ET  ET ET	
-			B44-6006-04	BADGE		
-			B44-6007-04	BADGE		
-			B46-0100-20	WARRANTY CARD		
-		*	B64-0083-00	INSTRUCTION MANUAL		
-		*	B64-0084-00	INSTRUCTION MANUAL		
14	1A	*	E30-3676-08	RCA CORD		
15	1A	*	E30-3677-08	DC CORD		
16	3A	*	F01-1372-08	HEAT SINK		
F1	1B		F05-2531-05	FUSE (25A)		
-		*	H01-9265-08	ITEM CARTON BOX		
-		*	H03-3306-08	OUTER PACKING CASE		
-		*	H10-4375-08	POLYSTYRENE FOAMED FIXTURE (L)		
-		*	H10-4376-08	POLYSTYRENE FOAMED FIXTURE (R)		
-			H25-0336-04	PROTECT. BAG (inst. & warrant.)		
-		*	H25-0341-04	PROTECTION BAG (for unit)		
35	1A	*	N99-1564-08	SCREW SET		
A	2A	*	N09-1945-05	SCREW (M3X8)		
B	2B		N09-4026-05	SCREW (4X8)		
C	2B		N15-1040-46	FLAT WASHER		
D	2A, 3B		N29-0053-05	LYLON RIVET		
E	1A, 1B		N35-3004-46	BINDING HEAD SCREW (M3X4)		
F	1B		N83-2608-45	BINDING HEAD SCREW (2.6X8)		
G	3A, 3B		N83-3005-45	BINDING HEAD SCREW (3X5)		
H	2A		N89-3006-45	BINDING HEAD TAPTITE (3X6)		
J	1A, 1B		N89-3008-45	BINDING HEAD TAPTITE (3X8)		
K	2A, 2B		N09-1467-05	SCREW (3X10)		
36	1A		W01-0701-05	TARMINAL SET	ET	
ELECTRIC CIRCUIT UNIT						
LED1			B30-1342-05	LED		
C1			CE04KW1E470M	ELECTRØ 47UF 25WV		
C2			C90-1634-05	ELECTRØ 3900UF 16WV		
C3 , 4			CF92FV1H104J	MF 0.10UF J		
C5			CK45FB1H102K	CERAMIC 1000PF K		
C6 , 7			CE04KW1E472M	ELECTRØ 4700UF 25WV		
C8			C90-2527-05	NP-ELECT 33UF 10WV		
C10			CF92FV1H102J	MF 1000PF J		
C11			CE04KW1C100M	ELECTRØ 10UF 16WV		
C12			CE04KW1E470M	ELECTRØ 47UF 25WV		
C13			CE04KW1E101M	ELECTRØ 100UF 25WV		
C14			CK45FB1H472K	CERAMIC 4700PF K		
C15			CE04KW1C330M	ELECTRØ 33UF 16WV		
C16 , 17			CE04KW1E470M	ELECTRØ 47UF 25WV		
C18			C90-2510-05	NP-ELECT 470UF 16WV		
C19			CE04KW1E471M	ELECTRØ 470UF 25WV		

E: Scandinavia &amp; Europe K: USA P: Canada W:Europe

Y: PX(Far East, Hawaii) T: England M: Other Areas

Y: AAFES(Europe) X: Australia

△ indicates safety critical components.

## PARTS LIST

\* New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

Ref. No.	Address	New Parts	Parts No.	Description	Destination	Remarks
参照番号	位置	新	部品番号	部品名 / 規格	仕向	備考
C21 , 22			CF92FV1H104J	MF 0.10UF J		
C23			CE04KW1C221M	ELECTRØ 220UF 16WV		
C101			CK45FB1H102K	CERAMIC 1000PF K		
C102			CE04KW1C100M	ELECTRØ 10UF 16WV		
C103			CC45FSL1H220J	CERAMIC 22PF J		
C104			CE04KW1A101M	ELECTRØ 100UF 10WV		
C105			CE04KW1H4R7M	ELECTRØ 4.7UF 50WV		
C106			CC45FSL1H681J	CERAMIC 680PF J		
C107			CC45FSL1H150J	CERAMIC 15PF J		
C108			CK45FB1H102K	CERAMIC 1000PF K		
C109			CC45FSL1H680J	CERAMIC 68PF J		
C110			CE04KW1A101M	ELECTRØ 100UF 10WV		
C115			CK45FF1H103Z	CERAMIC 0.010UF Z		
C116			CE04KW1H4R7M	ELECTRØ 4.7UF 50WV		
C117			CK45FF1H473Z	CERAMIC 0.047UF Z		
C118			CC45FSL1H471J	CERAMIC 470PF J		
C119			CE04KW1H2R2M	ELECTRØ 2.2UF 50WV		
C120			CC45FSL1H820J	CERAMIC 82PF J		
C121			CC45FSL1H820J	CERAMIC 82PF J		
C201			CK45FB1H102K	CERAMIC 1000PF K		
C202			CE04KW1C100M	ELECTRØ 10UF 16WV		
C203			CC45FSL1H220J	CERAMIC 22PF J		
C204			CE04KW1A101M	ELECTRØ 100UF 10WV		
C205			CE04KW1H4R7M	ELECTRØ 4.7UF 50WV		
C206			CC45FSL1H681J	CERAMIC 680PF J		
C207			CC45FSL1H150J	CERAMIC 15PF J		
C208			CK45FB1H102K	CERAMIC 1000PF K		
C209			CC45FSL1H680J	CERAMIC 68PF J		
C210			CE04KW1A101M	ELECTRØ 100UF 10WV		
C215			CK45FF1H103Z	CERAMIC 0.010UF Z		
C216			CE04KW1H4R7M	ELECTRØ 4.7UF 50WV		
C217			CK45FF1H473Z	CERAMIC 0.047UF Z		
C218			CC45FSL1H471J	CERAMIC 470PF J		
C219			CE04KW1H2R2M	ELECTRØ 2.2UF 50WV		
C220			CC45FSL1H820J	CERAMIC 82PF J		
C221			CC45FSL1H820J	CERAMIC 82PF J		
C301			CK45FB1H102K	CERAMIC 1000PF K		
C302			CE04KW1C100M	ELECTRØ 10UF 16WV		
C303			CC45FSL1H220J	CERAMIC 22PF J		
C304			CE04KW1A101M	ELECTRØ 100UF 10WV		
C305			CE04KW1H4R7M	ELECTRØ 4.7UF 50WV		
C306			CC45FSL1H681J	CERAMIC 680PF J		
C307			CC45FSL1H150J	CERAMIC 15PF J		
C308			CK45FB1H102K	CERAMIC 1000PF K		
C309			CC45FSL1H680J	CERAMIC 68PF J		
C310			CE04KW1A101M	ELECTRØ 100UF 10WV		
C315			CK45FF1H103Z	CERAMIC 0.010UF Z		
C316			CE04KW1H4R7M	ELECTRØ 4.7UF 50WV		
C317			CK45FF1H473Z	CERAMIC 0.047UF Z		
C318			CC45FSL1H471J	CERAMIC 470PF J		
C319			CE04KW1H2R2M	ELECTRØ 2.2UF 50WV		
C320			CC45FSL1H820J	CERAMIC 82PF J		
C321			CC45FSL1H820J	CERAMIC 82PF J		
C401			CK45FB1H102K	CERAMIC 1000PF K		
C402			CE04KW1C100M	ELECTRØ 10UF 16WV		

E: Scandinavia &amp; Europe K: USA P: Canada W:Europe

Y: PX(Far East, Hawaii) T: England M: Other Areas

Y: AAFES(Europe) X: Australia

△ indicates safety critical components.



## PARTS LIST

\* New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

Ref. No. 参照番号	Address 位置	New Parts 新	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕向	Re- marks 備考
C403			CC45FSL1H220J	CERAMIC 22PF J		
C404			CE04KW1A101M	ELECTRO 100UF 10WV		
C405			CE04KW1H4R7M	ELECTRO 4.7UF 50WV		
C406			CC45FSL1H681J	CERAMIC 680PF J		
C407			CC45FSL1H150J	CERAMIC 15PF J		
C408			CK45FB1H102K	CERAMIC 1000PF K		
C409			CC45FSL1H680J	CERAMIC 68PF J		
C410			CE04KW1A101M	ELECTRO 100UF 10WV		
C415			CK45FF1H103Z	CERAMIC 0.010UF Z		
C416			CE04KW1H4R7M	ELECTRO 4.7UF 50WV		
C417			CK45FF1H473Z	CERAMIC 0.047UF Z		
C418			CC45FSL1H471J	CERAMIC 470PF J		
C419			CE04KW1H2R2M	ELECTRO 2.2UF 50WV		
C420			CC45FSL1H820J	CERAMIC 82PF J		
C421			CC45FSL1H820J	CERAMIC 82PF J		
C501			CK45FF1H103Z	CERAMIC 0.010UF Z		
C601			CK45FF1H103Z	CERAMIC 0.010UF Z		
E1 ,2	2B		E06-0816-05	CYLINDRICAL RECEPTACLE	ET	
E3	2B		E20-0323-05	TERMINAL BOARD		
E4	2B	*	E63-0803-08	PHONE JACK		
E5	2B	*	E70-0801-05	TERMINAL BOARD		
J801		*	J21-7280-08	MOUNTING HARDWARE		
J802		*	J21-7281-08	MOUNTING HARDWARE		
L1		*	L33-0939-08	CHOKE COIL		
T1		*	L19-0514-08	TRANSFORMER		
R107-110			RN14BK2C1002F	RN 10.0K F 1/6W		
R131			RS14KB3DR22J	FL-PROOF RS 0.22 J 2W		
R132		*	RS14KB3DOR1J	FL-PROOF RS 0.1 J 2W		
R137			RS14KB2H100J	FL-PROOF RS 10 J 1/2W		
R207-210			RN14BK2C1002F	RN 10.0K F 1/6W		
R231			RS14KB3DR22J	FL-PROOF RS 0.22 J 2W		
R232		*	RS14KB3DOR1J	FL-PROOF RS 0.1 J 2W		
R237			RS14KB2H100J	FL-PROOF RS 10 J 1/2W		
R307-310			RN14BK2C1002F	RN 10.0K F 1/6W		
R331			RS14KB3DR22J	FL-PROOF RS 0.22 J 2W		
R332		*	RS14KB3DOR1J	FL-PROOF RS 0.1 J 2W		
R337			RS14KB2H100J	FL-PROOF RS 10 J 1/2W		
R407-410			RN14BK2C1002F	RN 10.0K F 1/6W		
R431			RS14KB3DR22J	FL-PROOF RS 0.22 J 2W		
R432		*	RS14KB3DOR1J	FL-PROOF RS 0.1 J 2W		
R437			RS14KB2H100J	FL-PROOF RS 10 J 1/2W		
VR101			R10-3638-08	POTENTIOMETER 10K(B)X2		
VR102			R12-2627-08	POTENTIOMETER 5K		
VR202			R12-2627-08	POTENTIOMETER 5K		
VR301			R10-3638-08	POTENTIOMETER 10K(B)X2		
VR302			R12-2627-08	POTENTIOMETER 5K		
VR402			R12-2627-08	POTENTIOMETER 5K		
SW101		*	S62-0805-08	SLIDE SWITCH		
SW301		*	S62-0805-08	SLIDE SWITCH		
D1			RM4Z	DIODE		
D2			FMU21S	DIODE		
D3			FMU21R	DIODE		

E: Scandinavia &amp; Europe K: USA P: Canada W: Europe

Y: PX(Far East, Hawaii) T: England M: Other Areas

Y: AAFES(Europe) X: Australia

⚠ indicates safety critical components.

## PARTS LIST

\* New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

Ref. No. 参照番号	Address 位置	New Parts 新	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕向	Re- marks 備考
D4 D5 D6 -9 D10 D11		*	1SS131 MTZJ5.1B 1SS131 MTZJ10C 1SS131	DIODE ZENER DIODE DIODE ZENER DIODE DIODE		
D14 ,15 D16 D102 D202 D302			1SR139 1SS131 1SS131 1SS131 1SS131	DIODE DIODE DIODE DIODE DIODE		
D402 IC1 IC2 IC3 IC101			1SS131 UPC494C NJM78M15FA NJM79M15FA NJM5532S	DIODE IC(SWITCHING REGULATOR) IC IC IC		
IC102 IC201 IC301 IC302 Q1 ,2			UPC4570HA UPC4570HA NJM5532S UPC4570HA 2SD809(F,E)	IC(OP AMP X2) IC(OP AMP X2) IC IC(OP AMP X2) TRANSISTOR		
Q3 ,4 Q5 -10 Q11 Q12 Q13 ,14		*	2SB1236 2SC4064 2SC1740S-R 2SA933S-R 2SC1740S-R	TRANSISTOR TRANSISTOR TRANSISTOR TRANSISTOR TRANSISTOR		
Q15 Q101 Q102,103 Q104,105 Q106		*	2SA933S-R 2SC3327-A 2SA1175(F) 2SC2785(F) 2SD1200(Q)	TRANSISTOR TRANSISTOR TRANSISTOR TRANSISTOR TRANSISTOR		
Q107 Q108 Q109 Q110 Q111		*	2SD1857 2SB1236 2SC4385(O,Y) 2SA1670(O,Y) 2SC1740S-R	TRANSISTOR TRANSISTOR TRANSISTOR TRANSISTOR TRANSISTOR		
Q201 Q202,203 Q204,205 Q206 Q207		*	2SC3327-A 2SA1175(F) 2SC2785(F) 2SD1200(Q) 2SD1857	TRANSISTOR TRANSISTOR TRANSISTOR TRANSISTOR TRANSISTOR		
Q208 Q209 Q210 Q211 Q301		*	2SB1236 2SC4385(O,Y) 2SA1670(O,Y) 2SC1740S-R 2SC3327-A	TRANSISTOR TRANSISTOR TRANSISTOR TRANSISTOR TRANSISTOR		
Q302,303 Q304,305 Q306 Q307 Q308		*	2SA1175(F) 2SC2785(F) 2SD1200(Q) 2SD1857 2SB1236	TRANSISTOR TRANSISTOR TRANSISTOR TRANSISTOR TRANSISTOR		
Q309 Q310 Q311 Q401 Q402,403		*	2SC4385(O,Y) 2SA1670(O,Y) 2SC1740S-R 2SC3327-A 2SA1175(F)	TRANSISTOR TRANSISTOR TRANSISTOR TRANSISTOR TRANSISTOR		

E: Scandinavia &amp; Europe K: USA P: Canada W: Europe

Y: PX(Far East, Hawaii) T: England M: Other Areas

Y: AAFES(Europe) X: Australia

⚠ indicates safety critical components.

## PARTS LIST

\* New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.


Teile ohne Parts No. werden nicht geliefert.

Ref. No. 参照番号	Address 位置	New Parts 新	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕向	Re- marks 備考
Q404,405			2SC2785(F)	TRANSISTOR		
Q406		*	2SD1200(Q)	TRANSISTOR		
Q407		*	2SD1857	TRANSISTOR		
Q408		*	2SB1236	TRANSISTOR		
Q409		*	2SC4385(O,Y)	TRANSISTOR		
Q410		*	2SA1670(O,Y)	TRANSISTOR		
Q411			2SC1740S-R	TRANSISTOR		
Q501			2SC3327-A	TRANSISTOR		
Q601			2SC3327-A	TRANSISTOR		
TH1		*	D103K4D-NHA109D	POSISTOR		

E: Scandinavia &amp; Europe K: USA P: Canada W: Europe

Y: PX(Far East, Hawaii) T: England M: Other Areas


Y: AAFES(Europe) X: Australia

 indicates safety critical components.

KAC-742



## PACKING



## SPECIFICATIONS

## Audio Section

Max Power Output [4Ω]	
4 Channel Mode .....	60 W × 4
3 Channel Mode .....	60 W × 2 + 130 W
2 Channel Mode .....	130 W × 2
Rated Power Output [4Ω]	
4 Channel Mode .....	30 W × 4 (20 Hz ~ 20 kHz, less than 0.08% THD)
3 Channel Mode .....	30 W × 2 (20 Hz ~ 20 kHz, 0.08%) + 80 W × 1 (1 kHz, 0.8%)
2 Channel Mode .....	80 W × 2 (1 kHz, 0.8% THD)
Rated Power Output [2 Ω]	
4 Channel Mode .....	40 W × 4 (1 kHz, 0.8% THD)
Frequency Response .....	4 ~ 64 kHz (−3 dB)
Signal to Noise Ratio .....	100 dB
Sensitivity (MAX) .....	0.1 V (rated output)
Sensitivity (MIN) .....	5.0 V (rated output)
Input Impedance .....	10 kΩ
Damping Factor (100 Hz) .....	More than 100

## General

Operating Voltage .....	14.4 V (11 ~ 16 V allowable)
Current Consumption (1 kHz, 10% THD) .....	33 A
Dimensions (W × H × D) .....	280 × 50 × 230 mm (11 × 1-15/16 × 9-1/16 in.)
Weight .....	3.0 kg (6.6 lb)

Kenwood follows a policy of continuous advancements in development. For this reason specifications may be changed without notice.

Kenwood poursuit une politique de progrès constants en ce qui concerne le développement. Pour cette raison, les spécifications sont sujettes à modifications sans préavis.

Kenwood strebt ständige, Verbesserungen in der Entwicklung an. Daher bleiben Änderungen der technischen Daten jederzeit vorbehalten.

## KENWOOD CORPORATION

Shionogi Shibuya Building, 17-5, 2-chome Shibuya, Shibuya-ku, Tokyo 150, Japan

## KENWOOD U.S.A. CORPORATION

2201 East Dominguez Street, Long Beach, CA 90810;  
550 Clark Drive, Mount Olive, NJ 07828, U.S.A.

## KENWOOD ELECTRONICS CANADA INC.

P.O. BOX 1075, 959 Gana Court, Mississauga, Ontario, Canada L4T 4C2

## TRIO-KENWOOD U.K. LTD.

KENWOOD House, Dwight Road, Watford, Herts., Wd1 8eb United Kingdom

## KENWOOD ELECTRONICS BENELUX N.V.

Mechelsesteenweg 418 B-1930 Zaventem, Belgium

## KENWOOD ELECTRONICS DEUTSCHLAND GMBH

Rembrücker-Str. 15, 6056 Heusenstamm, Germany

## TRIO-KENWOOD FRANCE S.A.

13 Boulevard Ney, 75018 Paris, France

## KENWOOD LINEAR S.p.A.

20125, MILANO-VIA ARBE, 50, ITALY

## KENWOOD ELECTRONICS AUSTRALIA PTY, LTD.

P.O. BOX 504, 8 Figtree Drive, Australia Centre, Homebush N.S.W. 2140, Australia

## KENWOOD &amp; LEE ELECTRONICS, LTD.

Wang Kee Building, 4th Floor, 34-37, Connaught Road, Central, Hong Kong